

Specifications	Rokit 5 G4	Rokit 7 G4	Rokit 8 G4	Rokit 10-3 G4
Configuration	2-Way	2-Way	2-Way	3-Way
Cabinet Type	Active Studio Monitor	Active Studio Monitor	Active Studio Monitor	Active Studio Monitor
Woofer	5.25" Kevlar® Aramid Fiber	6.5" Kevlar® Aramid Fiber	8" Kevlar® Aramid Fiber	5.25" Kevlar® Aramid Fiber
Mid Driver	N/A	N/A	N/A	4.5" Kevlar® Aramid Fiber
Tweeter	1" Kevlar® Aramid Fiber	1" Kevlar® Aramid Fiber	1" Kevlar® Aramid Fiber	1" Kevlar® Aramid Fiber
Frequency Response	43Hz - 400Hz	42Hz - 400Hz	35Hz - 400Hz	20Hz - 400Hz
Max. SPL	105dB SPL	110dB SPL	111dB SPL	112dB SPL
Amplifier Class	CLASS D	CLASS D	CLASS D	CLASS D
Power Output	25 Watts	145 Watts	203 Watts	300 Watts
THD (Frequency)	20 Watts	145 Watts	88 Watts	75 Watts
THD (Frequency)	N/A	N/A	N/A	75 Watts
THD (Frequency)	25 Watts	21 Watts	143 Watts	140 Watts
THD (Frequency)	5 Watts	5 Watts	5 Watts	5 Watts
Input Sensitivity	5.2VdB Balanced	5.1VdB Balanced	5.1VdB Balanced	5.1VdB Balanced
Unbalanced input, gain +12dB	+20dB	53dB - 50dB input, 52 dB, 0.035% THD+N	50dB - 50dB input, 52dB SW, 0.54% THD+N	31Hz - 10dB input, 10W SW, 0.01% THD+N
Balanced input, gain 0dB	+8dB	53dB - 48dB input, 73dB SW, 0.044% THD+N	50dB - 48dB input, 139W, 1.0% THD+N	31Hz - 48dB input, 11W, 0.07% THD+N
Control (all control parameters accessed via encoder and LCD)				
Volume control parameter	0.00dB to +11.0dB (default 0dB)	0.00dB to +11.0dB (default 0dB)	0.00dB to +11.0dB (default 0dB)	0.00dB to +11.0dB (default 0dB)
EQ Parameters				
EQ Control Selection 1	LOW SHELF (-24dB @ 60Hz)	LOW SHELF (-24dB @ 60Hz)	LOW SHELF (-24dB @ 60Hz)	LOW SHELF (-24dB @ 60Hz)
EQ Control Selection 2	LOW SHELF (-24dB @ 60Hz) and Low-Mid PEQ (-3dB @ 200Hz)	LOW SHELF (-24dB @ 60Hz) and Low-Mid PEQ (-3dB @ 200Hz)	LOW SHELF (-24dB @ 60Hz) and Low-Mid PEQ (-3dB @ 200Hz)	LOW SHELF (-24dB @ 60Hz) and Low-Mid PEQ (-3dB @ 200Hz)
EQ Control Selection 3	FLAT	FLAT	FLAT	FLAT
EQ Control Selection 4	LOW-MID PEQ (-3dB @ 200Hz)	LOW-MID PEQ (-3dB @ 200Hz)	LOW-MID PEQ (-3dB @ 200Hz)	LOW-MID PEQ (-3dB @ 200Hz)
EQ Control Selection 5	LOW SHELF (-24dB @ 60Hz)	LOW SHELF (-24dB @ 60Hz)	LOW SHELF (-24dB @ 60Hz)	LOW SHELF (-24dB @ 60Hz)
HF Control Selection 1	HIGH SHELF (-24dB @ 10 kHz)	HIGH SHELF (-24dB @ 10 kHz)	HIGH SHELF (-24dB @ 10 kHz)	HIGH SHELF (-24dB @ 10 kHz)
HF Control Selection 2	HIGH SHELF (-24dB @ 10 kHz) and LOW-MID PEQ (-3dB @ 3 kHz)	HIGH SHELF (-24dB @ 10 kHz) and LOW-MID PEQ (-3dB @ 3 kHz)	HIGH SHELF (-24dB @ 10 kHz) and LOW-MID PEQ (-3dB @ 3 kHz)	HIGH SHELF (-24dB @ 10 kHz) and LOW-MID PEQ (-3dB @ 3 kHz)
HF Control Selection 3	FLAT	FLAT	FLAT	FLAT
HF Control Selection 4	HIGH SHELF (-24dB @ 10 kHz) and LOW-MID PEQ (-3dB @ 3 kHz)	HIGH SHELF (-24dB @ 10 kHz) and LOW-MID PEQ (-3dB @ 3 kHz)	HIGH SHELF (-24dB @ 10 kHz) and LOW-MID PEQ (-3dB @ 3 kHz)	HIGH SHELF (-24dB @ 10 kHz) and LOW-MID PEQ (-3dB @ 3 kHz)
HF Control Selection 5	HIGH SHELF (-24dB @ 10 kHz)	HIGH SHELF (-24dB @ 10 kHz)	HIGH SHELF (-24dB @ 10 kHz)	HIGH SHELF (-24dB @ 10 kHz)
LED Parameters				
Backlight	Brightness adjustment from 0% to 100% (default 100%)	Brightness adjustment from 0% to 100% (default 100%)	Brightness adjustment from 0% to 100% (default 100%)	Brightness adjustment from 0% to 100% (default 100%)
Contrast	Contrast adjustment from 0% to 100% (default 50%)	Contrast adjustment from 0% to 100% (default 50%)	Contrast adjustment from 0% to 100% (default 50%)	Contrast adjustment from 0% to 100% (default 50%)
Standby	Standby on/off control (default on)	Standby on/off control (default on)	Standby on/off control (default on)	Standby on/off control (default on)
Input	Input on/off control (default on)	Input on/off control (default on)	Input on/off control (default on)	Input on/off control (default on)
Factory reset	Reset to factory setting defaults	Reset to factory setting defaults	Reset to factory setting defaults	Reset to factory setting defaults
Lock	Lock/Unlock control. When locked, all settings locked until unlocked.	Lock/Unlock control. When locked, all settings locked until unlocked.	Lock/Unlock control. When locked, all settings locked until unlocked.	Lock/Unlock control. When locked, all settings locked until unlocked.
Indicators				
Logic LED	Logic LED indicates Power on/Off, Standby function (status)	Logic LED indicates Power on/Off, Standby function (status)	Logic LED indicates Power on/Off, Standby function (status)	Logic LED indicates Power on/Off, Standby function (status)
LED Display	Displays all EQ and Setup Parameters	Displays all EQ and Setup Parameters	Displays all EQ and Setup Parameters	Displays all EQ and Setup Parameters
Connectors				
Input	Balanced TRS / XLR Combo Jack	Balanced TRS / XLR Combo Jack	Balanced TRS / XLR Combo Jack	Balanced TRS / XLR Combo Jack
Enclosure Construction	MDF	MDF	MDF	MDF
Finish	Black Vinyl Wrap	Black Vinyl Wrap	Black Vinyl Wrap	Black Vinyl Wrap
Mount Configuration	Front-Fire, Lock-out	Front-Fire, Lock-out	Front-Fire, Lock-out	Front-Fire, Lock-out
Dimensions (H x W x D)	11.22" (285mm) x 7.48" (190mm) x 9.49" (242mm)	11.31" (288mm) x 8.86" (225mm) x 11.19" (284mm)	15.75" (400mm) x 10.47" (266mm) x 12.17" (309mm)	21.50" (546mm) x 12.09" (307mm) x 14.6" (371mm)
Weight	10.99 lbs. (4.98 kg.)	16.76 lbs. (7.60 kg.)	22.76 lbs. (10.32 kg.)	16.05 lbs. (7.28 kg.)